

Watt Pilot - Motorized Attenuator, Enhanced Version

Typical Items

Wavelength, nm	Bandwidth, nm	Configuration	Optimization	Attenuation range* (T_{\min} - T_{\max}) @ CWL	Product ID
266	±5	$\lambda/2$ ZO waveplate + 2x TFP	Reflection	0.3-99%	EWP-R-0266
		$\lambda/2$ ZO waveplate + TFP	Transmission	0.5-95%	EWP-T-0266
343	±5	$\lambda/2$ ZO waveplate + 2x TFP	Reflection	0.3-99%	EWP-R-0343
		$\lambda/2$ ZO waveplate + TFP	Transmission	0.5-95%	EWP-T-0343
355	±5	$\lambda/2$ ZO waveplate + 2x TFP	Reflection	0.3-99%	EWP-R-0355
		$\lambda/2$ ZO waveplate + TFP	Transmission	0.5-95%	EWP-T-0355
515	±5	$\lambda/2$ ZO waveplate + 2x TFP	Reflection	0.3-99%	EWP-R-0515
		$\lambda/2$ ZO waveplate + TFP	Transmission	0.5-95%	EWP-T-0515
532	±5	$\lambda/2$ ZO waveplate + 2x TFP	Reflection	0.3-99%	EWP-R-0532
		$\lambda/2$ ZO waveplate + TFP	Transmission	0.5-95%	EWP-T-0532
1030	±10	$\lambda/2$ ZO waveplate + 2x Broadband TFP	Broadband Reflection	0.3-99%	EWP-R-1030
		$\lambda/2$ ZO waveplate + Broadband TFP	Broadband Transmission	0.5-95%	EWP-T-1030
1064	±5	$\lambda/2$ ZO waveplate + 2x TFP	Reflection	0.3-99%	EWP-R-1064
		$\lambda/2$ ZO waveplate + TFP	Transmission	0.5-95%	EWP-T-1064